

Example

# MIDI Machine Control

<b>by:</b>	Oliver Waits
<b>published:</b>	here (he submitted this by email)
<b>description:</b>	macros to send some MIDI commands which control MMC-enabled devices
<b>remarks:</b>	In order to run this over other ways than real 5pin MIDI Titan v13 is required

MIDI, MMC

## functions

- Panel.Midi.Send

The complete file with all commands/macros:

midimachinecontrolmacros.xml

## Code

MidiMachineControlShortlist.xml

```
<?xml version="1.0" encoding="utf-8"?>
<avolites.macros>

    <!-- MMC Stop -->
    <macro name="MMC Stop" id="Avolites.Macros.MMCTop">
        <sequence>
            <step>Panel.Midi.Send("F0 7F 7F 06 01 F7")</step>
        </sequence>
    </macro>

    <!-- MMC Play -->
    <macro name="MMC Play" id="Avolites.Macros.MMCPay">
        <sequence>
            <step>Panel.Midi.Send("F0 7F 7F 06 02 F7")</step>
        </sequence>
    </macro>

    <!-- MMC Pause -->
    <macro name="MMC Pause" id="Avolites.Macros.MMCPause">
        <sequence>
            <step>Panel.Midi.Send("F0 7F 7F 06 09 F7")</step>
        </sequence>
    </macro>

    <!-- MMC Goto Start -->
    <macro name="MMC Goto Start" id="Avolites.Macros.MMCGotoStart">
```

```
<sequence>
  <step>Panel.Midi.Send("F0 7F 7F 06 44 06 01 00 00 00 00 00 00
F7")</step>
</sequence>
</macro>

</avolites.macros>
```

## Explanation

This explains the functional steps within the sequence. For all the other XML details please refer to [Formats and syntax](#)

Upon starting such a macro a predefined MIDI command is being sent. For the available commands see [https://en.wikipedia.org/wiki/MIDI\\_Machine\\_Control](https://en.wikipedia.org/wiki/MIDI_Machine_Control) however it depends from the device/software which commands are supported.

The GoToStart macro is an example how to alter this to a particular timestamp:

- the message F0 7F 7F 06 44 06 01 00 00 00 00 F7 comprises of
  - F0 F7 ⇒ Universal Real Time SysEx
  - 7F ⇒ device ID. /F is all devices
  - 06 ⇒ MIDI machine control command
  - 44 ⇒ GoTo
  - 06 ⇒ length (6 bytes to follow)
  - 01 ⇒ target (usually 01)
  - 00 00 00 00 ⇒ hours minutes seconds frames aubframes (hexadecimal!)
  - F7 ⇒ end of Universal Real Time SysEx message

This way you can easily create your own macros to jump to a particular time: simply replace the 00 00 00 00 with the timestamp you want to jump to.

## How to use it

1. [make this macro available](#)
2. for general information about using MIDI to control other devices see [mmc\\_-\\_midi\\_machine\\_control](#)
3. depending from your setup you might need to use virtual MIDI patchcords like LoopMIDI or rtpMidi, see [Software List](#)
4. sending out MIDI e.g. over USB or network is supported from Titan v13 on

From:  
<https://avosupport.de/wiki/> - **AVOSUPPORT**

Permanent link:  
<https://avosupport.de/wiki/macros/example/midimachinecontrol?rev=1581582207>

Last update: **2020/02/13 08:23**

